


2. Check the software version that is currently installed on the camera (System – IP Camera Maintain – Software Version)



3. [Click here](#) to download NC110XB firmware files
4. Extract files from zip and copy
“NC110XB_NC305XB_NC317XB_NC312XC_V18.25.7.1_211129” folder to USB flash drive
5. Connect USB to NVR and watch YouTube video demonstrating how to perform the upgrade - <https://www.youtube.com/watch?v=leCP8InZpmE>
6. If the software version (as inspected in step 2) is V18.25.6.0_200904 or V18.25.6.0_200925 then upgrade to:

Step 1 - V18.25.6.0_201119. Wait approx. 3 minutes for FW to update

Once camera restarts and comes back online, then upgrade to:

Step 2 - V18.25.6.0_210301, wait approx. 3 minutes for FW to update


Once camera restarts and comes back online, then upgrade to:

Step 3 - V18.25.7.1_211129, wait approx. 3 minutes for FW to update


7. Once cameras come back online verify V18.25.7.1_211129 is now listed as the camera software version and default the cameras to confirm all settings take effect. (Refer to YouTube video from 3:30 – 4:20)

System – IP Camera Maintain – Load Default – Tick Cameras - Click **“Load Default”**.

You will be required to enter your NVR password for authentication



- For any future camera firmware updates, you will be able to perform an online update by Click system – IP Camera Maintain – Tick the camera and click Detect. If a new firmware version is available a popup message will appear



If you require additional support, please email service@ivsecurity.com.au with your NVR model, serial number, a brief description of the issue and your contact details.